

Factorizing one-loop contributions to two-loop Bhabha scattering and automatization of Feynman diagram calculations

J. Fleischer^{a,*}, O. V. Tarasov^{a,†}, T. Riemann^b and A. Werthenbach^b


^aUniversität Bielefeld, Fakultät für Physik, Universitätsstr. 25, 33615 Bielefeld, Germany

^bDESY Zeuthen, Platanenallee 6, 15738 Zeuthen, Germany

In higher order calculations a number of new technical problems arise: one needs diagrams in arbitrary dimension in order to obtain their needed ε -expansion, zero Gram determinants appear, renormalization produces diagrams with ‘dots’ on the lines, i.e. higher order powers of scalar propagators. All these problems cannot be accessed by the ‘standard’ Passarino-Veltman approach: there is not available what is needed for higher loops. We demonstrate our method of how to solve these problems.

1. DIANA

We are moving in the direction of **two-loop** Bhabha scattering, which is extremely important, in particular at higher energies, for the luminosity determination of the coming accelerators. By means of **DIANA** [1,2,3] we produced the following one-loop diagrams:



*J. Fleischer likes to thank CERN-INTAS for financial support under project no. INTAS-CERN 99-0377

†O.V. Tarasov likes to thank the DFG for financial support under project no. FL 241/4-2

Factorizing one-loop contributions are obtained e.g. in mass-renormalization: in any Feynman diagram we replace

$$\frac{1}{k^2 - (m^2 + \delta(m^2))} \rightarrow \frac{1}{k^2 - m^2} \left(1 + \frac{\delta(m^2)}{k^2 - m^2}\right),$$

thus obtaining ‘dotted’ diagrams.

2. Calculation of 1-loop integrals

The evaluation of one-loop integrals as used here was introduced in detail in [4]. The method exists in first reducing tensor integrals to scalar ones in higher dimension and higher indices (i.e. higher powers of scalar propagators). Before further reducing these scalar integrals already the on-shell conditions can be implemented and the amplitude decomposition performed. The reduction to ‘master integrals’ is performed by the use of recursion relations. One of these, reducing the space time dimension, is given by:

$$(d - \sum_{i=1}^n \nu_i + 1) \binom{0}{j}_n I_n^{(d+2)} = \left[\binom{0}{0}_n - \sum_{k=1}^n \binom{0}{k}_n \mathbf{k}^- \right] I_n^{(d)},$$

where the objects $\binom{i}{j}_n$ are Gram determinants. As a particular problem occurred in this connection zero Gram determinants, i.e. $\binom{0}{0}_n = 0$:

$$(d - \sum_{i=1}^n \nu_i + 1) \binom{0}{k}_n I_n^{(d+2)} = - \sum_{k=1}^n \binom{0}{k}_n \mathbf{k}^- I_n^{(d)}.$$

To increase again the dimension d , one then uses the relation

$$\sum_{j=1}^n \nu_j \mathbf{j}^+ I_n^{(d+2)} = -I_n^{(d)}.$$

3. Decomposition of the diagrams into Amplitudes

In order to avoid γ_5 , we decompose the amplitudes in terms of the following 12 structures:

$$\begin{aligned} O_1 &= I \cdot I, \quad O_2 = \hat{p}_4 \cdot I, \quad O_3 = I \cdot \hat{p}_2, \\ O_4 &= \hat{p}_4 \cdot \hat{p}_2, \quad O_5 = \gamma_\mu \cdot \gamma_\mu, \quad O_6 = \gamma_\mu \hat{p}_4 \cdot \gamma_\mu, \\ O_7 &= \gamma_\mu \cdot \gamma_\mu \hat{p}_2, \quad O_8 = \gamma_\mu \gamma_\nu \cdot \gamma_\nu \gamma_\mu, \\ O_9 &= \gamma_\mu \gamma_\nu \hat{p}_4 \cdot \gamma_\nu \gamma_\mu, \quad O_{10} = \gamma_\mu \gamma_\nu \cdot \gamma_\nu \gamma_\mu \hat{p}_2, \\ O_{11} &= \gamma_\mu \gamma_\nu \hat{p}_4 \cdot \gamma_\nu \gamma_\mu \hat{p}_2, \quad O_{12} = \gamma_\mu \gamma_\nu \gamma_\rho \cdot \gamma_\rho \gamma_\nu \gamma_\mu. \end{aligned}$$

Thus the on-shell diagrams read

$$\text{Diagram} = \sum_{j=1}^{12} \mathbf{A}_j \mathbf{O}_j.$$

with amplitudes $\mathbf{A}_j$. Finally we obtained ‘crossing relations’ like e.g. crossing diagrams 8 and 9 into each other:

$$\begin{aligned} A_1^{(9)} &= A_1^{(8)} - 2m_e A_7^{(8)} - 4m_e A_9^{(8)} + 2d A_8^{(8)} \\ A_2^{(9)} &= -A_2^{(8)} + 4A_7^{(8)} - 2(d-4)A_9^{(8)} - 8m_e A_{11}^{(8)} \\ A_3^{(9)} &= -A_3^{(8)} + 2A_6^{(8)} - 2(d-2)A_{10}^{(8)} - 4m_e A_{11}^{(8)} \\ A_4^{(9)} &= A_4^{(8)} - 2(d-2)A_{11}^{(8)} \\ A_5^{(9)} &= -A_5^{(8)} + 2m_e A_6^{(8)} + 4m_e A_7^{(8)} + 8m_e A_9^{(8)} \\ &\quad + 4m_e A_{10}^{(8)} - 12m_e^2 A_{11}^{(8)} - (6d-4)A_{12}^{(8)} \\ A_6^{(9)} &= -4m_e A_{11}^{(8)} + A_6^{(8)} \\ A_7^{(9)} &= -4m_e A_{11}^{(8)} + A_7^{(8)} \\ A_8^{(9)} &= -A_8^{(8)} \\ A_9^{(9)} &= A_9^{(8)} \\ A_{10}^{(9)} &= A_{10}^{(8)} \\ A_{11}^{(9)} &= -A_{11}^{(8)} \\ A_{12}^{(9)} &= A_{12}^{(8)} \end{aligned}$$

and **exchanging $\mathbf{t}$ and $\mathbf{u}$** . These relations also hold for crossing diagrams 7 to 10 ($\mathbf{s}$ and $\mathbf{u}$ exchanged). For the crossing of 7 and 8 ($\mathbf{s}$ and $\mathbf{t}$ exchanged) only a change of sign occurs in the amplitudes. **Thus:** we need to calculate **only one** selfenergy, vertex and box.

Further relations between amplitudes of **one** diagram (obtained by solving a system of equations) are:

$$\begin{aligned} A_3 &= A_2 \\ A_7 &= A_6 \\ A_{10} &= A_9 \\ A_8 &= \frac{1}{4}A_1 - \frac{m_e}{2}A_2 + (A_{12}) \\ A_9 &= \frac{1}{4m_e}A_1 - \frac{1}{2}A_2 - \frac{1}{2}A_6 \\ A_{11} &= \frac{1}{4m_e^2}A_1 - \frac{1}{2m_e}A_2 \end{aligned}$$

Thus: there are only **6 independent amplitudes**.

The amplitudes for any of the diagrams, even for non-zero electron mass, are relatively short. They were presented in the talk and can be obtained from ACAT’s webpage [5]. What remains to do is to expand the master integrals, given in arbitrary d , in ε , ($d = 4 - 2\varepsilon$) in order to obtain properly all finite contributions. This work is presently being done.

REFERENCES

1. M. Tentyukov and J. Fleischer, ”A Feynman diagram analyser DIANA”, Comput. Phys. Commun. 132 (2000) 124.
2. M. Tentyukov and J. Fleischer, talk given at 6th International Workshop AIHENP 99, Heraklion, Crete, Greece, hep-ph/9905560.
3. J. Fleischer and M. Tentyukov, ”A Feynman diagram analyser DIANA: Graphic facilities”, talk given at the VII’t International Workshop, ACAT2000, Fermilab, AIP Conference Proceedings, vol. 583, hep-ph/0012189.
4. J. Fleischer, F. Jegerlehner and O.V. Tarasov, Nucl.Phys. B566 (2000) 423.
5. <http://acat02.sinp.msu.ru/presentations/fleischer/ACAT.ps>